

Overview

HPE FlexFabric 5945 Switch Series

HPE FlexFabric 5945 Switch Series is a family of high-density, ultra-low-latency, and ToR switches that is part of the HPE FlexFabric solution (from the HPE Cloud-First Reference Architecture).

Ideally suited for deployment at the aggregation or server access layer of large enterprise data centers, the HPE FlexFabric 5945 Switch Series is also powerful enough for deployment at the core layer of medium-sized enterprises.

With the increase in virtualized applications and server-to-server traffic, customers require spine and ToR switches that can meet their throughput requirements. With the HPE FlexFabric 5945, data centers can now support up to 100 Gb per port, allowing high-performance server connectivity and the capabilities to handle virtual environments. This is available in the low-latency HPE FlexFabric 5945 Switch Series..



HPE FlexFabric 5945 48SFP28 8QSFP28 Switch (JQ074A)



HPE FlexFabric 5945 4-slot Switch (JQ076A)

Overview



HPE FlexFabric 5945 2-slot Switch (JQ075A)



HPE FlexFabric 5945 32QSFP28 Switch (JQ077A)

Models

HPE FlexFabric 5945 48SFP28 8QSFP28 Switch	JQ074A
HPE FlexFabric 5945 4-slot Switch	JQ076A
HPE FlexFabric 5945 2-slot Switch	JQ075A
HPE FlexFabric 5945 32QSFP28 Switch	JQ077A

Key Features

- Cut-through with ultra low latency and wirespeed
 - VXLAN, VTEP, and OVSDDB support for virtualized environments
 - High-density 100GbE/40GbE/25GbE/10GbE spine/top-of-rack (ToR) connectivity
 - IPv6 support with full L2 and L3 features
 - HPE FlexFabric Network Analytics solution support for real-time microburst detection
-

Standard Features

Quality of Service (QoS) Powerful QoS Features

- **Flexible queue scheduling**
Including Strict Priority (SP), WRR, WFQ, SP+WRR, SP+WDRR, SP+WFQ, configurable buffer, time range, queue shaping, and CAR with 8 kbps granularity.
- **Packet filtering and remarking**
Packet filtering based on packet header fields from Layer 2 through Layer 4, including source MAC, destination MAC, source IP (IPv4/IPv6), destination IP (IPv4/IPv6), port number, protocol type, and VLAN.

Data center Optimized

- **Flexible high port density**
HPE FlexFabric 5945 Switch Series enables scaling of the server edge, with 100GbE, 40GbE, 25GbE, and 10GbE spine and leaf deployment. The HPE FlexFabric 5945 Switch Series solution includes a 48-port of 25 Gb with 8-port of , 32-port of 100 Gb and 2 modular models of respectively 1RU / 2-slot and 2RU / 4-slot
- **High-performance switching**
Cut-through and nonblocking architecture delivers low latency (~ 1 microsecond for 100GbE) for very demanding enterprise applications; the switch delivers high-performance switching capacity and wirespeed packet forwarding
- **Higher scalability**
HPE Intelligent Resilient Fabric (IRF) technology simplifies the architecture of server access networks; up to 10 HPE FlexFabric 5945 switches can be combined to deliver unmatched scalability of virtualized access layer switches and flatter 2-tier networks using HPE IRF, which reduces cost and complexity
- **Advanced modular operating system**
Comware v7 software's modular design and multiple processes bring native high stability, independent process monitoring, and restart; the OS also allows individual software modules to be upgraded for higher availability and supports enhanced serviceability functions such as hitless software upgrades with HPE IRF based in-service software upgrade (ISSU)
- **Reversible airflow**
Enhanced for data center hot-cold aisle deployment with reversible airflow-for either front-to-back or back-to-front airflow
- **Redundant fans and power supplies**
Internal redundant and hot-pluggable power supplies and dual fan trays enhance reliability and availability
- **Lower OPEX and greener data center**
Provides reversible airflow and advanced chassis power management
- **Data Center Bridging (DCB) protocols**
Provides support for IEEE 802.1Qbb Priority Flow Control (PFC), Data Center Bridging Exchange (DCBX), IEEE 802.1Qaz Enhanced Transmission Selection (ETS), Explicit Congestion Notification (ECN) for converged FCoE, iSCSI, and RoCE environments
- **Jumbo frames**
With frame sizes of up to 9416 bytes on 100GbE ports, high-performance remote backup and disaster recovery services are enabled
- **VXLAN hardware support**
VXLAN L2/L3 gateway support for up to 4K tunnels
- **Dynamic VXLAN configuration**
OVSDB support for dynamic VXLAN configuration

Convergence

- **LLDP-MED (Media Endpoint Discovery)**
Defines a standard extension of LLDP that stores values for parameters such as QoS and VLAN to configure network devices such as IP phones automatically

Standard Features

Manageability

The HPE FlexFabric Network Analytics solution with real-time telemetry analysis provides insight into data center network operation

- Tracks all the accounting associated with the admission and allocation process of all the buffers and queues across the ingress and egress ports
- Microburst congestion detection
- Rich congestion analytics
- Buffer congestion state and statistics
- For more information, see the [HPE FlexFabric Network Analytics data sheet](#) and [HPE FlexFabric Network Analytics technical white paper](#).
- **Full-featured console**
Provides complete control of the switch with a familiar CLI
- **Troubleshooting**
 - **Ingress and egress port monitoring:** Enable network problem solving
 - **Traceroute and ping:** Enable testing of network connectivity
- **Multiple configuration files**
Allow multiple configuration files to be stored to a flash image
- **sFlow® (RFC 3176)**
Provides wirespeed traffic accounting and monitoring
- **SNMP v1, v2c, and v3**
Facilitates centralized discovery, monitoring, and secure management of networking devices
- **Out-of-band interface**
Isolates management traffic from user data plane traffic for complete isolation and total reachability, no matter what happens in the data plane
- **Remote configuration and management**
Delivered through a secure CLI over Telnet and SSH; role-based access control (RBAC) provides multiple levels of access; configuration rollback and multiple configurations on the flash provide ease of operation; remote visibility is provided with sFlow and SNMP v1/v2/v3, and is fully supported in [HPE Intelligent Management Center \(IMC\)](#)
- **ISSU and hot patching**
Provides hitless software upgrades with IRF-based ISSU and hitless patching of the modular operating system
- **PTP and NTP support**

Synchronizes timekeeping among distributed time servers and clients; support for Precision Time Protocol (PTP) and Network Time Protocol (NTP)

Layer 2 switching

- **Address Resolution Protocol (ARP)**
Supports static, dynamic, and reverse ARP and ARP proxy
- **IEEE 802.3x Flow Control**
Provides intelligent congestion management via PAUSE frames
- **Ethernet Link Aggregation**

Provides IEEE 802.3ad Link Aggregation of up to 256 groups of 32 ports; support for LACP, LACP Local Forwarding First, and LACP Short-time provide a fast, resilient environment that is ideal for the data center

- **Spanning Tree Protocol**
Supports STP (IEEE 802.1D), Rapid STP (RSTP, IEEE 802.1w), and Multiple STP (MSTP, IEEE 802.1s)
 - **VLAN support**
Provides support for 4096 VLANs based on port
-

Standard Features

- **IGMP support**

Provides support for IGMP Snooping, fast-leave, and group policy; IPv6 IGMP Snooping provides L2 optimization of multicast traffic

- **DHCP support at L2**

Provides full DHCP Snooping support for DHCP Snooping Option 82, DHCP Relay Option 82, DHCP Snooping Trust, and DHCP Snooping Item Backup

Resiliency and high availability

- **IRF technology**

Enables an HPE FlexFabric switch to deliver resilient, scalable, and secured data center networks for physical and virtualized environments; groups up to 10 HPE FlexFabric 5945 switches in an HPE IRF configuration, allowing them to be configured and managed as a single switch with a single IP address; simplifies ToR deployment and management, reducing data center deployment and operating expenses

- **IEEE 802.1w Rapid Convergence Spanning Tree Protocol**

Increases network uptime through faster recovery from failed links

- **IEEE 802.1s Multiple Spanning Tree**

Provides high-link availability in multiple VLAN environments by allowing Multiple Spanning Trees

- **Virtual Router Redundancy Protocol (VRRP)**

Allows groups of two routers to back each other up dynamically to create highly available routed environments

- **Hitless patch upgrades**

Allows patches and new service features to be installed without restarting the equipment, increasing network uptime, and facilitating maintenance

- **Fast protocol convergence with standard-based failure detection-Bidirectional Forwarding Detection (BFD)**

Enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF

- **Device Link Detection Protocol (DLDP)**

Monitors link connectivity and shuts down ports at both ends if unidirectional traffic is detected, preventing loops in STP-based networks

- **Graceful restart**

Allows routers to indicate to others their capability to maintain a routing table during a temporary shutdown and significantly reduces convergence times upon recovery; supports OSPF, BGP, and IS-IS

Layer 3 services

- **Address Resolution Protocol**

Determines the MAC address of another IP host in the same subnet; supports static ARPs; gratuitous ARP allows detection of duplicate IP addresses; proxy ARP allows normal ARP operation between subnets or when subnets are separated by a L2 network

- **Dynamic Host Configuration Protocol**

Simplifies the management of large IP networks and supports client and server; DHCP Relay enables DHCP operation across subnets

- **Operations, administration, and maintenance (OAM) support**

Provides support for Connectivity Fault Management (IEEE 802.1AG) and Ethernet in the First Mile (IEEE 802.3AH); provides additional monitoring that can be used for fast fault detection and recovery

Security

- **Access control lists**

Provides IP L3 filtering based on source/destination IP, address/subnet, and source/destination TCP/UDP port number

Standard Features

- **RADIUS/TACACS+**
Eases switch management security administration by using a password authentication server
- **Secure shell**
Encrypts all transmitted data for secure remote CLI access over IP networks
- **IEEE 802.1X and RADIUS network logins**
Controls port-based access for authentication and accountability
- **Port security**
Allows access only to specified MAC addresses, which can be learned or specified by the administrator

Layer 3 routing

- **EVPN and EVPN-DCI**
Can act as a VTEP, EVPN Gateway, or Border Gateway enabling virtual multipoint bridged connectivity between different Layer 2 domains over an IP network
- **VRRP and VRRP Extended**
Allows quick failover of router ports
- **Policy-based routing**
Makes routing decisions based on policies set by the network administrator
- **Equal-Cost Multipath (ECMP)**
Enables multiple equal-cost links in a routing environment to increase link redundancy and scale bandwidth
- **L3 IPv4 routing**
Provides routing of IPv4 at media speed; supports static routes, RIP and RIPv2, OSPF, BGP, and IS-IS
- **Open shortest path first**
Delivers faster convergence; uses this link-state routing interior gateway protocol (IGP), which supports ECMP, NSSA, and MD5 authentication for increased security and graceful restart for faster failure recovery
- **Border Gateway Protocol 4 (BGP-4)**
Delivers an implementation of the BGP utilizing path vectors; uses TCP for enhanced reliability for the route discovery process; reduces bandwidth consumption by advertising only incremental updates; supports extensive policies for increased flexibility; scales to very large networks
- **Intermediate system to intermediate system (IS-IS)**
Uses a path vector IGP, which is defined by the ISO organization for IS-IS routing and extended by IETF RFC 1195 to operate in both TCP/IP and the OSI reference model (integrated IS-IS)
- **Static IPv6 routing**
Provides simple manually configured IPv6 routing
- **Dual IP stack**
Maintains separate stacks for IPv4 and IPv6 to ease the transition from an IPv4-only network to an IPv6-only network design
- **Routing Information Protocol next generation (RIPng)**
Extends RIPv2 to support IPv6 addressing
- **OSPFv3**
Provides OSPF support for IPv6
- **BGP+**
Extends BGP-4 to support Multiprotocol BGP (MBGP), including support for IPv6 addressing
- **IS-IS for IPv6**
Extends IS-IS to support IPv6 addressing
- **IPv6 tunneling**
Allows IPv6 packets to traverse IPv4-only networks by encapsulating the IPv6 packet into a standard IPv4 packet; supports manually configured, 6 to 4, and intra-site automatic tunnel addressing protocol (ISATAP) tunnels; is an important element for the transition from IPv4 to IPv6
- **Policy routing**
Allows custom filters for increased performance and security; supports ACLs, IP prefix, AS paths, community lists, and aggregate policies

Standard Features

- **Bidirectional Forwarding Detection (BFD)**
Enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF
 - **Multicast Routing PIM dense and sparse modes**
Provides robust support of multicast protocols
 - **Layer 3 IPv6 routing**
Provides routing of IPv6 at media speed; supports static routing, RIPng, OSPFv3, BGP4+ for IPv6, and IS-ISv6
-

Management

- **USB support**
 - **File copy:** Allows users to copy switch files to and from a USB flash drive
 - **Multiple configuration files**
Stores easily to the flash image
 - **SNMPv1, v2c, and v3**
Facilitates centralized discovery, monitoring, and secure management of networking devices
 - **Out-of-band interface**
Isolates management traffic from user data plane traffic for complete isolation and total reachability, no matter what happens in the data plane
 - **Port mirroring**
Enables traffic on a port to be simultaneously sent to a network analyzer for monitoring
 - **Remote configuration and management**
Is available through a CLI
 - **IEEE 802.1AB Link Layer Discovery Protocol (LLDP)**
Advertises and receives management information from adjacent devices on a network, facilitating easy mapping by network management applications
 - **sFlow (RFC 3176)**
Provides scalable ASIC-based wirespeed network monitoring and accounting with no impact on network performance; this allows network operators to gather a variety of sophisticated network statistics and information for capacity planning and real-time network monitoring purposes
 - **Command authorization**
Leverages RADIUS to link a custom list of CLI commands to an individual network administrator's login; an audit trail documents activity
 - **Dual flash images**
Provides independent primary and secondary operating system files for backup while upgrading
 - **Command-line interface**
Provides a secure, easy-to-use CLI for configuring the module via SSH or a switch console; provides direct real-time session visibility
 - **Logging**
Provides local and remote logging of events via SNMP (v2c and v3) and syslog; provides log throttling and log filtering to reduce the number of log events generated
 - **Management interface control**
Provides management access through a modem port and terminal interface, as well as in-band and out-of-band Ethernet ports; provides access through terminal interface, Telnet, or SSH
 - **Industry-standard CLI with a hierarchical structure**
Reduces training time and expenses, and increases productivity in multivendor installations
 - **Management security**
Restricts access to critical configuration commands; offers multiple privilege levels with password protection; ACLs provide Telnet and SNMP access; local and remote syslog capabilities allow logging of all access
 - **Information center**
Provides a central repository for system and network information; aggregates all logs, traps, and debugging information generated by the system and maintains them in order of severity; outputs the network information to multiple channels based on user-defined rules
-

Standard Features

- **Network management**
HPE IMC centrally configures, updates, monitors, and troubleshoots
 - **Remote intelligent mirroring**
Mirrors ingress/egress ACL-selected traffic from a switch port or VLAN to a local or remote switch port anywhere on the network
-

Additional information

- **Green IT and power**
Improves energy efficiency through the use of the latest advances in silicon development; shuts off unused ports and utilizes variable-speed fans, reducing energy costs
-

Warranty and support

- **1-year warranty**
See <http://www.hpe.com/networking/warrantysummary> for warranty and support information included with your product purchase.
 - **Software releases**
To find software for your product, refer to <http://www.hpe.com/networking/support>; for details on the software releases available with your product purchase, refer to <http://www.hpe.com/networking/warrantysummary>
-

Configuration Information

BTO Models

Rule #	Description	SKU
1, 2, 3, 4, 5, 6, 7, 8	Standard Switch Enclosures HPE FlexFabric 5945 48SFP28 8QSFP28 Switch <ul style="list-style-type: none"> • 48 SFP/SFP+/SFP28 ports (min=0 \ max=48) • 8 QSFP+/QSFP28 ports (min=0 \ max=8) • 3 SFP Management Port (min=0 \ max=3) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ074A
1, 2, 5, 6	HPE FlexFabric 5945 2-slot Switch <ul style="list-style-type: none"> • 2 port expansion module slots • 1 SFP Management Port (min=0 \ max=1) • 2 QSFP+/QSFP28 (min=0 \ max=2) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ075A
1, 2	HPE FlexFabric 5945 4-slot Switch <ul style="list-style-type: none"> • 4 port expansion module slots • 3 SFP Management Port (min=0 \ max=3) • 4 Power Supply Slots (Min 2 required) • 2 Fan Tray Slots (Min 2 required) • 2U - Height 	JQ076A
1, 2, 5, 6, 7, 8	HPE FlexFabric 5945 32QSFP28 Switch <ul style="list-style-type: none"> • 32 QSFP+/QSFP28 ports (min=0 \ max=32) • 3 SFP Management Port (min=0 \ max=3) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ077A
Configuration Rules		
1	The following SFP/SFP+ Transceivers install into this Switch's Management Ports and SFP+ Ports: HPE X115 100M SFP LC FX Transceiver HPE X110 100M SFP LC LX Transceiver	JD102B JD120B
2	The following SFP Transceivers install into this switch's Management Port and SFP+ Ports: HPE X120 1G SFP LC SX Transceiver HPE X120 1G SFP LC LX Transceiver HPE X120 1G SFP LC LH100 Transceiver HPE X120 1G SFP RJ45 T Transceiver	JD118B JD119B JD103A JD089B
3	The following SFP+ Transceivers install into this Switch: HPE X130 10G SFP+ LC BiDi 10km-Uplink Transceiver HPE X130 10G SFP+ LC BiDi 10km-Downlink Transceiver HPE X130 10G SFP+ LC BiDi 40km-Uplink Transceiver HPE X130 10G SFP+ LC BiDi 40km-Downlink Transceiver HPE X130 10G SFP+ LC SR Transceiver HPE X130 10G SFP+ LC LR Transceiver HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL737A JL738A JL739A JL740A JD092B JD094B JL290A JL291A JL292A

Configuration Information

Rule #	Description	SKU
	HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
4	The following SFP28 Transceivers install into this Switch:	
	HPE X190 25G SFP28 LC SR 100m MM Transceiver	JL293A
	HPE X240 25G SFP28 to SFP28 1m Direct Attach Copper Cable	JL294A
	HPE X240 25G SFP28 to SFP28 3m Direct Attach Copper Cable	JL295A
	HPE X240 25G SFP28 to SFP28 5m Direct Attach Copper Cable	JL296A
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A
5	The following QSFP+ Transceivers install into this Switch:	
	HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
	HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
6	The following QSFP28 Transceivers install into this Switch:	
	HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
	HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419A
	HPE X150 100G QSFP28 LC BiDi 100m MM Transceiver	JQ344A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672A
	HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
	HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
	HPE X150 100G QSFP28 CWDM4 2km SM Transceiver	JH673A
	HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
	HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
	HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
	HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
	HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
	HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
Notes:	Selection Form - HPE Offering > DataCenter Networking > FlexFabric Switches - Access: HPE FlexFabric 5945 Switch Series	

Configuration Information

7	<p>The following QSFP28 Transceivers install into this Switch:</p> <p>HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable JL282A HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable JL283A HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable JL284A</p>
8	<p>The following QSFP28 Transceivers install into this Switch:</p> <p>HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable JG329A HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable JG330A HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable JG331A</p>

Rack Level Integration CTO Models

CTO Switch Chassis

Rule #	Description	SKU
1, 2, 3, 4, 5, 6, 7, 8	<p>HPE FlexFabric 5945 48SFP28 8QSFP28 Switch</p> <ul style="list-style-type: none"> • 48 SFP/SFP+/SFP28 ports (min=0 \ max=48) • 8 QSFP+/QSFP28 ports (min=0 \ max=8) • 3 SFP Management Port (min=0 \ max=3) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ074A
1, 2, 5, 6	<p>HPE FlexFabric 5945 2-slot Switch</p> <ul style="list-style-type: none"> • 2 port expansion module slots • 1 SFP Management Port (min=0 \ max=1) • 2 QSFP+/QSFP28 (min=0 \ max=2) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ075A
1, 2	<p>HPE FlexFabric 5945 4-slot Switch</p> <ul style="list-style-type: none"> • 4 port expansion module slots • 3 SFP Management Port (min=0 \ max=3) • 4 Power Supply Slots (Min 2 required) • 2 Fan Tray Slots (Min 2 required) • 2U - Height 	JQ076A
1, 2, 5, 6, 7, 8	<p>HPE FlexFabric 5945 32QSFP28 Switch</p> <ul style="list-style-type: none"> • 32 QSFP+/QSFP28 ports (min=0 \ max=32) • 3 SFP Management Port (min=0 \ max=3) • 2 Power Supply Slots (Min 1 required) • 5 Fan Tray Slots (Min 5 required) • 1U - Height 	JQ077A

Configuration Rules

Rule #	Description	SKU
1	<p>The following SFP/SFP+ Transceivers install into this Switch's Management Ports and SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable</p> <p>HPE X115 100M SFP LC FX Transceiver JD102B HPE X110 100M SFP LC LX Transceiver JD120B</p>	
2	<p>The following SFP Transceivers install into this switch's Management Ports and SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable</p>	

Configuration Information

	HPE X120 1G SFP LC SX Transceiver	JD118B
	HPE X120 1G SFP LC LX Transceiver	JD119B
	HPE X120 1G SFP LC LH100 Transceiver	JD103A
	HPE X120 1G SFP RJ45 T Transceiver	JD089B
3	The following SFP+ Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X130 10G SFP+ LC BiDi 10km-Uplink Transceiver	JL737A
	HPE X130 10G SFP+ LC BiDi 10km-Downlink Transceiver	JL738A
	HPE X130 10G SFP+ LC BiDi 40km-Uplink Transceiver	JL739A
	HPE X130 10G SFP+ LC BiDi 40km-Downlink Transceiver	JL740A
	HPE X130 10G SFP+ LC SR Transceiver	JD092B
	HPE X130 10G SFP+ LC LR Transceiver	JD094B
	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
	HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
	HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
4	The following SFP28 Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X190 25G SFP28 LC SR 100m MM Transceiver	JL293A
	HPE X240 25G SFP28 to SFP28 1m Direct Attach Copper Cable	JL294A
	HPE X240 25G SFP28 to SFP28 3m Direct Attach Copper Cable	JL295A
	HPE X240 25G SFP28 to SFP28 5m Direct Attach Copper Cable	JL296A
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A
5	The following QSFP+ Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
	HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
	HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
6	The following QSFP28 Transceivers install into this Switch: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
	HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419A
	HPE X150 100G QSFP28 LC BiDi 100m MM Transceiver	JQ344A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672A
	HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A

Configuration Information

HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X150 100G QSFP28 CWDM4 2km SM Transceiver	JH673A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A

7 If HPE CTO Switch Chassis is selected for Rack Level Integration, Then the Switch needs to integrate (with #0D1) to the Rack.

Notes: Clic UNB - If an option is ordered with #0D1/#B01, then the switch must have #0D1 option.

Switch Options

Enter the following menu selections as integrated to the CTO Model X server above if order is factory built.

Rule #	Description	SKU
	Modules	
	(JQ076A) System (std 0 // max 4) User Selection (min 1 // max 4)	
1, 2, 7, 8, 11, 12, 15	HPE 5930 24-port SFP+ and 2-port QSFP+ Module 24 1G/10G SFP/SFP+ ports (min=0 \ max=24) 2 40G QSFP+ ports (min=0 \ max=2)	JH180A
1, 2, 7, 8, 11, 12, 15	HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module <ul style="list-style-type: none"> 24 1G/10G SFP/SFP+ ports (min=0 \ max=24) 2 40G QSFP+ ports (min=0 \ max=2) 	JH181A
2, 8, 11	HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MACsec Module <ul style="list-style-type: none"> 24 1/10GBase-T ports 2 40G QSFP+ ports (min=0 \ max=2) 	JH182A
2, 8, 11	HPE 5930 8-port QSFP+ Module <ul style="list-style-type: none"> 8 40G QSFP+ ports (min=0 \ max=8) 	JH183A
1, 2, 7, 8, 11, 12, 13, 15	HPE 5930 24-port Converged Port and 2-port QSFP+ Module <ul style="list-style-type: none"> 24 Converged 1G/10G SFP/SFP+ 8G FC ports (min=0 \ max=24) 2 40G QSFP+ ports (min=0 \ max=2) 	JH184A
3, 8, 11	HPE 5950 16-port QSFP+ Module <ul style="list-style-type: none"> 16 40G QSFP+ ports (min=0 \ max=16) 	JH405A

Notes: 4x10GbE Splitter Cables are not supported

Configuration Information

Rule #	Description	SKU
2, 8, 9, 11	HPE 5950 8-port QSFP28 Module <ul style="list-style-type: none"> 8 40G/100G QSFP+/QSFP28 ports (min=0 \ max=8) 	JH406A
1, 2, 4, 7, 8, 9, 10, 11, 12, 15	HPE FlexFabric 5950 24-port SFP28 and 2-port QSFP28 Module <ul style="list-style-type: none"> 24 10G/25G SFP+/SFP28 ports (min=0 \ max=24) (Default) 2 40G/100G QSFP+/QSFP28 ports (min=0 \ max=2) 	JH450A
2, 9, 11	HPE FlexFabric 5950 8-port QSFP28 MACsec Module <ul style="list-style-type: none"> 8 40G/100G QSFP+/QSFP28 ports (min=0 \ max=8) 	JH957A
Configuration Rules		
1	The following Transceivers install into this Module's SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable HPE X130 10G SFP+ LC BiDi 10km-Uplink Transceiver HPE X130 10G SFP+ LC BiDi 10km-Downlink Transceiver HPE X130 10G SFP+ LC BiDi 40km-Uplink Transceiver HPE X130 10G SFP+ LC BiDi 40km-Downlink Transceiver HPE X130 10G SFP+ LC SR Transceiver HPE X130 10G SFP+ LC LR Transceiver HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JL737A JL738A JL739A JL740A JD092B JD094B JD095C JD096C JD097C JG081C
2	The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver HPE X140 40G QSFP+ MPO SR4 Transceiver HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver HPE X140 40G QSFP+ LC ER4 40km SM Transceiver HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG661A JL251A JG325B JG709A JL286A JL306A JG326A JG327A JG328A JG329A JG330A JG331A
3	The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver HPE X140 40G QSFP+ MPO SR4 Transceiver HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver HPE X140 40G QSFP+ LC ER4 40km SM Transceiver HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG661A JL251A JG325B JG709A JL286A JL306A JG326A JG327A JG328A

Configuration Information

Rule #	Description	SKU
7	The following 10G Transceivers install into this Module's SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
	HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
8	The following 40G Transceivers install into this Module's QSFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
9	The following 100G Transceivers install into this Module's QSFP28 Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
	HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419A
	HPE X150 100G QSFP28 LC BiDi 100m MM Transceiver	JQ344A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672A
	HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
	HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
	HPE X150 100G QSFP28 CWDM4 2km SM Transceiver	JH673A
	HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
	HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
	HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
	HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
	HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
	HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
	HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
	HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
10	The following SFP28 Transceivers install into this Module's SFP28 Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X190 25G SFP28 LC SR 100m MM Transceiver	JL293A
	HPE X240 25G SFP28 to SFP28 1m Direct Attach Copper Cable	JL294A
	HPE X240 25G SFP28 to SFP28 3m Direct Attach Copper Cable	JL295A
	HPE X240 25G SFP28 to SFP28 5m Direct Attach Copper Cable	JL296A
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A
11	The following 40G Transceiver installs into this Module's QSFP+ Ports with PHY: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
12	The following 10G Transceiver installs into this Module's SFP+ Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable	
	HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
	HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
13	Fibre channel support is 8Gb/4Gb/2Gb on any of the 24 converged ports of the JH184A Module. Note that a maximum of 8Gb FC is supported regardless of the FC optics used.	

Configuration Information

15 The following Transceivers install into this Module's (SFP28) Ports: (Use #0D1 or #B01 if switch is CTO) - if applicable

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC LH100 Transceiver	JD103A

Transceivers

Rule #	Description	SKU
	SFP Transceivers	
	HPE X115 100M SFP LC FX Transceiver	JD102B
	HPE X110 100M SFP LC LX Transceiver	JD120B
	HPE X120 1G SFP RJ45 T Transceiver	JD089B
	HPE X120 1G SFP LC SX Transceiver	JD118B
	HPE X120 1G SFP LC LX Transceiver	JD119B
	HPE X120 1G SFP LC LH100 Transceiver	JD103A
Notes:	1G transceivers are supported in all Management Ports as well as SFP Ports, SFP+ Ports and SFP28 Ports.	
	100M Transceivers are supported ONLY in SFP or Management Ports, not in any SFP+ or SFP28 ports.	
	SFP+ Transceivers	
	HPE X130 10G SFP+ LC BiDi 10km-Uplink Transceiver	JL737A
	HPE X130 10G SFP+ LC BiDi 10km-Downlink Transceiver	JL738A
	HPE X130 10G SFP+ LC BiDi 40km-Uplink Transceiver	JL739A
	HPE X130 10G SFP+ LC BiDi 40km-Downlink Transceiver	JL740A
	HPE X130 10G SFP+ LC SR Transceiver	JD092B
	HPE X130 10G SFP+ LC LR Transceiver	JD094B
	HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
	HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
	HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
	HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
	SFP28 Transceivers	
	HPE X190 25G SFP28 LC SR 100m MM Transceiver	JL293A
	HPE X240 25G SFP28 to SFP28 1m Direct Attach Copper Cable	JL294A
	HPE X240 25G SFP28 to SFP28 3m Direct Attach Copper Cable	JL295A
	HPE X240 25G SFP28 to SFP28 5m Direct Attach Copper Cable	JL296A
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A

Rule #	Description	SKU
	QSFP+ Transceivers	
	HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B

Configuration Information

HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

QSFP28 Transceivers

HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274A
HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419A
HPE X150 100G QSFP28 LC BiDi 100m MM Transceiver	JQ344A
HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672A
HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420A
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275A
HPE X150 100G QSFP28 CWDM4 2km SM Transceiver	JH673A
HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276A
HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277A
HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278A
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273A
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284A

Internal Power Supplies

(JQ074A, JQ075A and JQ077A) System (std 0 // max 2) User Selection (min 1 // max 2)

(JQ076A) System (std 0 // max 4) User Selection (min 2 // max 4)

1, 2, 3	HPE 58x0AF 650W AC Power Supply	JC680A
	<ul style="list-style-type: none"> includes 1 x c13, 650w 	
	HPE 58x0AF 650W AC Power Supply PDU Cable NA/JP/TW	JC680A#B2B
	<ul style="list-style-type: none"> C15 PDU Jumper Cord (NA/MX/TW/JP) 	
	HPE 58x0AF 650W AC Power Supply PDU Cable ROW	JC680A#B2C
	<ul style="list-style-type: none"> C15 PDU Jumper Cord (ROW) 	
	HPE A58x0AF 650W AC Power Supply	JC680A#AC3
	<ul style="list-style-type: none"> No Localized Power Cord Selected 	
1, 3	HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A
	<ul style="list-style-type: none"> includes 1 x c13, 650w 	

Configuration Information

Configuration Rules

Rule #	Description
1	PSU's cannot be mixed in the same switch enclosure
2	Localization (Wall Power Cord) required on orders without #B2B, #B2C, and #AC3 (PDU Power Cord) . (See Localization Menu) REMARK: When Switches/Routers are Factory Racked, Then #B2B, or #B2C should be the Defaulted Power Cable option on the Switches/Routers.
3	Must be ordered in multiples of 2 if configuring with JQ076A
Notes:	Drop down under power supply should offer the following options and results: Switch/Router to PDU Power Cord - #B2B in NA, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO) Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO) No Power Cord - #AC3 Option

Fan Trays

(JQ074A, JQ075A and JQ077A) System (std 0 // max 5) User Selection (min 5 // max 5)

(JQ076A) System (std 0 // max 2) User Selection (min 2 // max 2)

Rule #	Description	SKU
1, 2	HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume 2 Fan Tray	JH389A
1, 2	HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume 2 Fan Tray	JH388A
1, 3	HPE 5930 4-slot Back (Power Side) to Front (Port Side) Airflow Fan Tray	JH185A
1, 3	HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Tray	JH186A

Configuration Rules

1	Fan Trays cannot be mixed in the same switch enclosure	
2	This fan tray is supported on: HPE FlexFabric 5945 48SFP28 8QSFP28 Switch HPE FlexFabric 5945 2-slot Switch HPE FlexFabric 5945 32QSFP28 Switch	JQ074A JQ075A JQ077A
3	This fan tray is supported on: HPE FlexFabric 5945 4-slot Switch	JQ076A

Notes: If there is any empty space below the switch (JQ075A) in a rack when using Back to Front Fan Tray, JH389A, the rack will receive an Air Plenum kit that takes up 1U of additional space in the rack. The Air Plenum kit is not required on fully configured racks. The Air Plenum Kit is a non-saleable SKU, and is brought in automatically for CTO Factory Rack Level Integration.

If there is any empty space below the switch (JQ076A) in a rack when using Back to Front Fan Tray, JH185A, the rack will receive an Air Plenum kit that takes up 1U of additional space in the rack. The Air Plenum kit is not required on fully configured racks. The Air Plenum Kit is a non-saleable SKU, and is brought in automatically for CTO Factory Rack Level Integration.

Related Options

HPE FlexFabric 5945 Switch Series accessories

Remarks	Description	SKU
	HPE FlexFabric 5945 48SFP28 8QSFP28 Switch (JQ074A) accessories	
	HPE 58x0AF 650W AC Power Supply	JC680A
	HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A
	HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume 2 Fan Tray	JH389A
	HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume 2 Fan Tray	JH388A
	HPE FlexFabric 5945 4-slot Switch (JQ076A) accessories	
	HPE 58x0AF 650W AC Power Supply	JC680A
	HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A
	HPE 5930 4-slot Back (Power Side) to Front (Port Side) Airflow Fan Tray	JH185A
	HPE 5930 4-slot Front (Port Side) to Back (Power Side) Airflow Fan Tray	JH186A
	HPE FlexFabric 5945 32QSFP28 Switch (JQ077A) accessories	
	HPE 58x0AF 650W AC Power Supply	JC680A
	HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A
	HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume 2 Fan Tray	JH389A
	HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume 2 Fan Tray	JH388A
	HPE FlexFabric 5945 2-slot Switch (JQ075A) accessories	
	HPE 58x0AF 650W AC Power Supply	JC680A
	HPE FlexFabric Switch 650W 48V Hot Plug NEBS-compliant DC Power Supply	JH336A
	HPE X712 Back (Power Side) to Front (Port Side) Airflow High Volume 2 Fan Tray	JH389A
	HPE X711 Front (Port Side) to Back (Power Side) Airflow High Volume 2 Fan Tray	JH388A
	HPE FlexFabric 5945 2-slot Switch (JQ075A) and 4-slot Switch (JQ076A) I/O modules	
	HPE 5930 24-port SFP+ and 2-port QSFP+ Module	JH180A
	HPE 5930 24-port SFP+ and 2-port QSFP+ with MACsec Module	JH181A
	HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MACsec Module	JH182A
	HPE 5930 8-port QSFP+ Module	JH183A
	HPE 5930 24-port Converged Port and 2-port QSFP+ Module	JH184A
	HPE 5950 16-port QSFP+ Module	JH405A
	HPE 5950 8-port QSFP28 Module	JH406A
	HPE FlexFabric 5950 24-port SFP28 and 2-port QSFP28 Module	JH450A
	HPE FlexFabric 5950 8-port QSFP28 MACsec Module	JH957A

HPE FlexFabric 5945 Switch Optics

Remarks	Description	SKU
	Gigabit SFP transceiver modules	
	HPE X120 1G SFP RJ45 T Transceiver	JD089B
	HPE X120 1G SFP LC SX Transceiver	JD118B
	HPE X120 1G SFP LC LX Transceiver	JD119B
	HPE X120 1G SFP LC LH100 Transceiver	JD103A
Notes:	1G transceivers are supported in all Management Ports as well as SFP Ports, SFP+ Ports and SFP28 Ports.	
	100-Megabit SFP transceiver modules	
	HPE X115 100M SFP LC FX Transceiver	JD102B
	HPE X110 100M SFP LC LX Transceiver	JD120B
Notes:	100M Transceivers are supported in all Management Ports and SFP Ports; not supported in SFP+ ports.	

Related Options

10-Gigabit SFP+ modules and cables

Remarks	Description	SKU
	10-Gigabit SFP+ transceiver modules available for the SFP+ ports and SFP28 ports	
	HPE X130 10G SFP+ LC SR Transceiver	JD092B
	HPE X130 10G SFP+ LC LR Transceiver	JD094B
	HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
	HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
	HPE X130 10G SFP+ LC BiDi 10km-Uplink Transceiver	JL737A
	HPE X130 10G SFP+ LC BiDi 10km-Downlink Transceiver	JL738A
	HPE X130 10G SFP+ LC BiDi 40km-Uplink Transceiver	JL739A
	HPE X130 10G SFP+ LC BiDi 40km-Downlink Transceiver	JL740A
	10-Gigabit SFP+ fiber cables available for the SFP+ ports and SFP28 ports	
	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable	JL290A
	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable	JL291A
	HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable	JL292A
	10-Gigabit SFP+ copper cables available for the SFP+ ports and SFP28 ports	
	HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C

25-Gigabit SFP28 modules and cables

Remarks	Description	SKU
	SFP28 transceiver modules available for the SFP28 ports	
	HPE X190 25G SFP28 LC SR 100m MM Transceiver	JL293A
	SFP28 active optical cables available for the SFP28 ports	
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A
	SFP28 copper cables available for the SFP28 ports	
	HPE X240 25G SFP28 to SFP28 1m Direct Attach Copper Cable	JL294A
	HPE X240 25G SFP28 to SFP28 3m Direct Attach Copper Cable	JL295A
	HPE X240 25G SFP28 to SFP28 5m Direct Attach Copper Cable	JL296A
	SFP28 fiber cables available for the SFP28 ports	
	HPE X2A0 25G SFP28 to SFP28 3m Active Optical Cable	JH955A
	HPE X2A0 25G SFP28 to SFP28 5m Active Optical Cable	JH956A
	HPE X2A0 25G SFP28 to SFP28 7m Active Optical Cable	JL297A
	HPE X2A0 25G SFP28 to SFP28 10m Active Optical Cable	JL298A
	HPE X2A0 25G SFP28 to SFP28 20m Active Optical Cable	JL299A

40-Gigabit QSFP+ modules and cables

Related Options

Remarks	Description	SKU
	QSFP+ transceiver modules available for the QSFP+ and QSFP28 ports	
	HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
	HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver	JL286A
	HPE X140 40G QSFP+ LC ER4 40km SM Transceiver	JL306A
	QSFP+ fiber cables available for the QSFP+ and QSFP28 ports	
	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable	JL287A
	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable	JL288A
	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable	JL289A
	QSFP+ copper cables available for the QSFP+ and QSFP28 ports	
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
	QSFP+ to 4 x SFP+ copper cables available for the QSFP+ and QSFP28 ports	
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

100-Gigabit QSFP28 modules and cables

Remarks	Description	SKU
	QSFP28 transceiver modules available for the QSFP28 ports	
	HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver	JL274 A
	HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419 A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672 A
	HPE X150 100G QSFP28 MPO PSM4 500m SM Transceiver	JH420 A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672 A
	HPE X150 100G QSFP28 LC LR4 10km SM Transceiver	JL275 A
	HPE X150 100G QSFP28 CWDM4 2km SM Transceiver	JH673 A
	HPE X150 100G QSFP28 LC SWDM4 100m MM Transceiver	JH419 A
	HPE X150 100G QSFP28 eSR4 300m MM Transceiver	JH672 A
	QSFP28 fiber cables available for the QSFP28 ports	
	HPE X2A0 100G QSFP28 to QSFP28 7m Active Optical Cable	JL276 A
	HPE X2A0 100G QSFP28 to QSFP28 10m Active Optical Cable	JL277 A

Related Options

HPE X2A0 100G QSFP28 to QSFP28 20m Active Optical Cable	JL278 A
QSFP28 copper cables available for the QSFP28 ports	
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable	JL271 A
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable	JL272 A
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable	JL273 A
QSFP28 to SFP28 copper cables available for the QSFP28 ports	
HPE X240 QSFP28 4xSFP28 1m Direct Attach Copper Cable	JL282 A
HPE X240 QSFP28 4xSFP28 3m Direct Attach Copper Cable	JL283 A
HPE X240 QSFP28 4xSFP28 5m Direct Attach Copper Cable	JL284 A

Software

Rule#	Orchestrator Description	SKU
1, 2	HPE IMC Orchestrator Base E-LTU	JL849AAE
1, 3	HPE IMC Orchestrator Analyzer Add-on E-LTU	JL850AAE
1, 4	HPE IMC Orchestrator Network Node Add-on E-LTU	JL851AAE
1, 3	HPE IMC Orchestrator Analyzer IP Host Add-on E-LTU	JL852AAE
Configuration Rules		
Rule #	Description	
1	When configuring 12900 Switch Chassis(JH262A or JL255A), this Orchestrator Service is available when one of the following Type X MPUs is added: HPE FlexFabric 12904E Type X Main Processing Unit HPE FlexFabric 12900E Type X Main Processing Unit	JL844A JL845A
2	IMC Orchestrator Base E-LTU sku must be Qty 1 per solution	
3	If this analyzer E-LTU is selected, then Qty 1 must be added per solution. Additionally, if this Analyzer E-LTU is selected, then IP Host E-LTU must match qty of desired Hosts.	
4	This Network Node Add-on E-LTU must match the switch qty in the solution	

Technical Specifications

HPE FlexFabric 5945 48SFP28 8QSFP28 Switch (JQ074A)		
I/O ports and slots	48 x 25G SFP28 ports 8 x 100G QSFP28 ports 2 x 1G SFP ports Supports 48 x 10/25GbE and 8 x 100GbE fixed ports, or up to 80 x 10GbE ports when using splitter cables	
Additional ports and slots	1 x console port 1 x mini USB port 1 x USB port 2 x out-of-band management ports (one fiber port and one copper port)	
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	
Fan tray	5 fan tray slots The customer must order fan trays, as they are not included with the switch. This system requires same-direction airflow fan trays to function properly. The system should not be operated with less than five fan trays for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
Physical characteristics	Dimensions	43.6 x 440 x 460 mm (1.72 x 17.32 x 18.11 in)
	Weight	10.10 kg (22.27 lb) shipping weight
	Full configuration weight	15 kg (33.07 lb)
Memory and processor	1 GB flash; packet buffer size: 32 MB, 8 GB SDRAM	
Performance	Latency	< 1 μs (64-byte packets)
	Throughput	2024 Mpps
	Routing/Switching capacity	4 Tbps
	Routing table size	324K entries (IPv4), 162K entries (IPv6)
	MAC address table size	288K entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C)
	Operating relative humidity	5% to 95%, noncondensing
	Acoustic	Low-speed fan: 62.1 dB, high-speed fan: 77.9 dB
Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	1381 BTU/hr (1458 kJ/hr)
	Voltage	100 VAC to 240 VAC V rated 90 VAC to 264 VAC max
		-40 VDC to -60 VDC rated -40 VDC to -72 VDC max
	Maximum power rating	650 W
	Idle power	179 W
	Notes: Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated	
Safety	UL 60950-1, CAN/CSA C22.2 No 60950-1, IEC 60950-1, EN 60950-1, AS/NZS 60950-1, FDA 21 CFR Subchapter J	
Emissions	FCC Part 15 (CFR 47) CLASS A, ICES-003 CLASS A, VCCI CLASS A, CISPR 32 CLASS A, EN 55032 CLASS A, AS/NZS CISPR32 CLASS A, EN 61000-3-2, EN 61000-3-3, ETSI EN 300 386	

Technical Specifications

Immunity	CISPR 24, EN 55024, ETSI EN 300 386
Management	IMC; CLI; out-of-band management; SNMP Manager; Telnet; FTP Notes: The customer must install a minimum of one power supply, as the device does not come with one. The customer must install 5 fan kits, as the device does not come with one.
Services	Refer to the Hewlett Packard Enterprise website at: http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE FlexFabric 5945 4-slot Switch (JQ076A)		
I/O ports and slots	4 module slots 2 x 1G SFP ports Type 1000BASE-LX Supports up to a maximum of 96 x 10/25GbE and 8 x 100GbE ports, or up to 32 x 100GbE ports	
Additional ports and slots	1 x console port 1 x mini USB port 1 x USB port 2 x out-of-band management ports (one fiber port and one copper port)	
Power supplies	4 power supply slots 2 minimum power supplies required (ordered separately)	
Fan tray	2 fan tray slots The customer must order fan trays, as they are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
Physical characteristics	Dimensions	88.1 x 440 x 660 mm (3.47 x 17.32 x 25.98 in) (2U height)
	Weight	18.10 kg (39.90 lb) shipping weight
	Full configuration weight	27 kg (59.52 lb)
Memory and processor	1 GB flash; packet buffer size: 32 MB, 8 GB SDRAM	
Performance	Latency	< 1 μs (64-byte packets)
	Throughput	2024 Mbpps
	Routing/Switching capacity	6.4 Tbps
	Routing table size	324K entries (IPv4), 162K entries (IPv6)
	MAC address table size	288K entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C)
	Operating relative humidity	5% to 95%, noncondensing
	Acoustic	Low-speed fan: 70.8 dB, high-speed fan: 83.2dB
Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	2348 BTU/hr (2478 kJ/hr)
	Voltage	100 VAC to 240 VAC V rated, 90 VAC to 264 VAC max., -40 VDC to -60 VDC rated -40 VDC to -72 VDC max.
	Maximum power rating	650 W
	Idle power	185 W
	Notes: Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case	

Technical Specifications

	theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated
Safety	UL 60950-1, CAN/CSA C22.2 No 60950-1, IEC 60950-1, EN 60950-1, AS/NZS 60950-1, FDA 21 CFR Subchapter J
Emissions	FCC Part 15 (CFR 47) CLASS A, ICES-003 CLASS A, VCCI CLASS A, CISPR 32 CLASS A, EN 55032 CLASS A, AS/NZS CISPR32 CLASS A, EN 61000-3-2, EN 61000-3-3, ETSI EN 300 386
Immunity	CISPR 24, EN 55024, ETSI EN 300 386
Management	IMC; CLI; out-of-band management; SNMP Manager; Telnet; FTP Notes: The customer must install a minimum of two power supplies, as the device does not come with one. The customer must install 2 fan kits, as the device does not come with one.
Services	Refer to the Hewlett Packard Enterprise website at: http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE FlexFabric 5945 32QSFP28 Switch (JQ077A)		
I/O ports and slots	32 x 100G QSFP28 ports 2 x 1G SFP ports	
Additional ports and slots	1 x console port 1 x mini USB port 1 x USB port 2 x out-of-band management ports (one fiber port and one copper port)	
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	
Fan tray	5 fan tray slots The customer must order fan trays, as they are not included with the switch. This system requires same-direction airflow fan trays to function properly. The system should not be operated with less than five fan trays for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
Physical characteristics	Dimensions	43.6 x 440 x 460 mm (1.72 x 17.32 x 18.11 in)
	Weight	10.4 kg (22.93 lb) shipping weight
Memory and processor	1 GB flash; packet buffer size: 32 MB, 8 GB SDRAM	
Performance	Latency	< 1 μs (64-byte packets)
	Throughput	2024 Mpps
	Routing/Switching capacity	6.4 Tbps
	Routing table size	324K entries (IPv4), 162K entries (IPv6)
	MAC address table size	288K entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C)
	Operating relative humidity	5% to 95%, noncondensing
	Acoustic	Low-speed fan: 62.4 dB, high-speed fan: 78.1 dB
Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	1283 BTU/hr (1458 kJ/hr)
	Voltage	100 VAC to 240 VAC V rated 90 VAC to 264 VAC max
		-40 VDC to -60 VDC rated -40 VDC to -72 VDC max

Technical Specifications

	Maximum power rating	650 W
	Idle power	154 W
	<p>Notes: Idle power is the actual power consumption of the device with no ports connected.</p> <p>Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated</p>	
Safety	UL 60950-1, CAN/CSA C22.2 No 60950-1, IEC 60950-1, EN 60950-1, AS/NZS 60950-1, FDA 21 CFR Subchapter J	
Emissions	FCC Part 15 (CFR 47) CLASS A, ICES-003 CLASS A, VCCI CLASS A, CISPR 32 CLASS A, EN 55032 CLASS A, AS/NZS CISPR32 CLASS A, EN 61000-3-2, EN 61000-3-3, ETSI EN 300 386	
Immunity	CISPR 24, EN 55024, ETSI EN 300 386	
Management	IMC; CLI; out-of-band management; SNMP Manager; Telnet; FTP	
	<p>Notes: The customer must install a minimum of one power supply, as the device does not come with one. The customer must install 5 fan kits, as the device does not come with one.</p>	
Services	Refer to the Hewlett Packard Enterprise website at: http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

HPE FlexFabric 5945 2-slot Switch (JQ075A)		
I/O ports and slots	2 module slots 2 x 100G QSFP28 ports Supports up to a maximum of 48 x 10/25GbE and 4 x 100GbE ports, or up to 16 x 100GbE ports	
Additional ports and slots	1 x console port 1 x mini USB port 1 x USB port 2 x out-of-band management ports (one fiber port and one copper port)	
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	
Fan tray	5 fan tray slots The customer must order fan trays, as they are not included with the switch. This system requires same-direction airflow fan trays to function properly. The system should not be operated with with less than five fan trays for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	
Physical characteristics	Dimensions	44.2 x 440 x 660 mm (1.74 x 17.32 x 25.98 in.)
	Weight	13.10 kg (28.88 lb) shipping weight
Memory and processor	1 GB flash; packet buffer size: 32 MB, 8 GB SDRAM	
Performance	Latency	< 1 μs (64-byte packets)
	Throughput	2024 Mbpps
	Routing/Switching capacity	3.6 Tbps
	Routing table size	324K entries (IPv4), 162K entries (IPv6)
	MAC address table size	288K entries
Environment	Operating temperature	32°F to 113°F (0°C to 45°C)
	Operating relative humidity	5% to 95%, noncondensing
	Acoustic	Low-speed fan: 70.8 dB, high-speed fan: 83.2dB

Technical Specifications

Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	1392 BTU/hr (1458 kJ/hr)
	Voltage	100 VAC to 240 VAC V rated, 90 VAC to 264 VAC max., -40 VDC to -60 VDC rated -40 VDC to -72 VDC max.
	Maximum power rating	650 W
	Idle power	136 W
	<p>Notes: Idle power is the actual power consumption of the device with no ports connected.</p> <p>Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated</p>	
Safety	UL 60950-1, CAN/CSA C22.2 No 60950-1, IEC 60950-1, EN 60950-1, AS/NZS 60950-1, FDA 21 CFR Subchapter J	
Emissions	FCC Part 15 (CFR 47) CLASS A, ICES-003 CLASS A, VCCI CLASS A, CISPR 32 CLASS A, EN 55032 CLASS A, AS/NZS CISPR32 CLASS A, EN 61000-3-2, EN 61000-3-3, ETSI EN 300 386	
Immunity	CISPR 24, EN 55024, ETSI EN 300 386	
Management	IMC; CLI; out-of-band management; SNMP Manager; Telnet; FTP	
	<p>Notes: The customer must install a minimum of two power supplies, as the device does not come with one. The customer must install five fan kits, as the device does not come with any.</p>	
Services	Refer to the Hewlett Packard Enterprise website at: http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

Standards and protocols

Applies to all products in series

- IEEE 802.1ad Q-in-Q
- IEEE 802.1AX-2008 Link Aggregation
- IEEE 802.1D MAC Bridges
- IEEE 802.1p Priority
- IEEE 802.1Q VLANs
- IEEE 802.1s Multiple Spanning Trees
- IEEE 802.1w Rapid Reconfiguration of Spanning Tree
- IEEE 802.3ad Link Aggregation Control Protocol (LACP)
- IEEE 802.3ae 10-Gigabit Ethernet
- IEEE 802.3ag Ethernet OAM
- IEEE 802.3ah Ethernet in First Mile over Point to Point Fiber-EFMM
- IEEE 802.3x Flow Control RFC 768 UDP
- RFC 783 TFTP Protocol (revision 2)
- RFC 791 IP
- RFC 792 ICMP
- RFC 793 TCP
- RFC 826 ARP
- RFC 854 Telnet
- RFC 856 Telnet
- RFC 868 Time Protocol
- RFC 896 Congestion Control in IP/TCP Internetworks
- RFC 950 Internet Standard Subnetting Procedure
- RFC 1027 Proxy ARP
- RFC 1058 RIPv1
- RFC 1091 Telnet Terminal-Type Option
- RFC 1141 Incremental updating of the internet checksum
- RFC 1142 OSI IS-IS Intra-domain Routing Protocol

Technical Specifications

- RFC 1191 Path MTU discovery
- RFC 1213 Management Information Base for Network Management of TCP/IP-based internet RFC 1253 (OSPF v2)
- RFC 1531 DHCP
- RFC 1533 DHCP Options and BOOTP Vendor Extensions
- RFC 1534 DHCP/BOOTP Interoperation
- RFC 1541 DHCP
- RFC 1542 Clarifications and Extensions for the Bootstrap Protocol
- RFC 1591 DNS (client only)
- RFC 1624 Incremental internet Checksum
- RFC 1723 RIP v2
- RFC 1812 IPv4 Routing
- RFC 2030 Simple Network Time Protocol (SNTP) v4
- RFC 2131 DHCP
- RFC 2236 IGMP Snooping
- RFC 2338 VRRP
- RFC 2453 RIPv2
- RFC 2581 TCP Congestion Control
- RFC 2644 Directed Broadcast Control
- RFC 2767 Dual Stacks IPv4 & IPv6
- RFC 2865 RADIUS
- RFC 2868 RADIUS Attributes for Tunnel Protocol Support
- RFC 2890 Key and Sequence Number Extensions to GRE
- RFC 3046 DHCP Relay Agent Information Option
- RFC 3411 An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks
- RFC 3412 Message Processing and Dispatching for the Simple Network Management Protocol (SNMP)
- RFC 3413 SNMP Applications
- RFC 3416 Protocol Operations for SNMP
- RFC 3417 Transport Mappings for the SNMP
- RFC 3418 Management Information Base (MIB) for the SNMP
- RFC 3768 VRRP
- RFC 4250 The SSH) Protocol Assigned Numbers
- RFC 4251 The SSH Protocol Architecture
- RFC 4252 The SSH Authentication Protocol
- RFC 4253 The SSH Transport Layer Protocol
- RFC 4254 The SSH Connection Protocol
- RFC 4292 IP Forwarding Table MIB
- RFC 4293 Management Information Base for the Internet Protocol (IP)
- RFC 4364 BGP/MPLS IP Virtual Private Networks (VPNs)
- RFC 4419 Diffie-Hellman Group Exchange for the SSH Transport Layer Protocol
- RFC 4594 Configuration Guidelines for DiffServ Service Classes
- RFC 4601 Protocol Independent Multicast- Sparse Mode (PIM-SM): Protocol Specification (Revised)
- RFC 4604 Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicast
- RFC 4607 Source-Specific Multicast for IP
- RFC 4941 Privacy Extensions for Stateless Address Auto configuration in IPv6
- RFC 5340 OSPF for IPv6
- RFC 5905 NTP Version 4: Protocol and Algorithms Specification
- RFC 2929 RADIUS Support DS for RADIUS

Device Management

- RFC 1157 SNMPv1/v2c
- RFC 1305 NTPv3

Technical Specifications

- RFC 1591 DNS (client)
 - RFC 1902 (SNMPv2)
 - RFC 1908 (SNMP v1/2 Coexistence)
 - RFC 2573 (SNMPv3 Applications)
 - RFC 2576 (coexistence between SNMP V1, V2, V3)
 - RFC 2819 RMON
 - Multiple configuration files
 - Multiple software images
 - SSHv1/SSHv2 Secure Shell
 - TACACS/TACACS+
-

IPv6

- RFC 2080 RIPng for IPv6
 - RFC 2460 IPv6 Specification
 - RFC 2461 IPv6 Neighbor Discovery
 - RFC 2462 IPv6 Stateless Address Auto-configuration
 - RFC 2463 ICMPv6
 - RFC 2464 Transmission of IPv6 over Ethernet Networks
 - RFC 2473 Generic Packet Tunneling in IPv6
 - RFC 2545 Use of MP-BGP-4 for IPv6
 - RFC 2563 ICMPv6
 - RFC 2711 IPv6 Router Alert Option
 - RFC 2740 OSPFv3 for IPv6
 - RFC 2767 Dual stacks IPv4 & IPv6
 - RFC 3315 DHCPv6 (client and relay)
 - RFC 3484 Default Address Selection for IPv6
 - RFC 3810 Multicast Listener Discovery Version 2 (MLDv2) for IPv6
 - RFC 4213 Basic Transition Mechanisms for IPv6 Hosts and Routers
 - RFC 4291 IP Version 6 Addressing Architecture
 - RFC 4443 ICMPv6
 - RFC 4552 Authentication/Confidentiality for OSPFv3
 - RFC 4862 IPv6 Stateless Address Auto-configuration
 - RFC 5095 Deprecation of Type 0 Routing Headers in IPv6
-

BGP

- RFC 1163 BGP
 - RFC 1771 BGPv4
 - RFC 1997 BGP Communities Attribute
 - RFC 2918 Route Refresh Capability
 - RFC 3392 Capabilities Advertisement with BGP-4
 - RFC 4271 A BGP 4 (BGP-4)
 - RFC 4360 BGP Extended Communities Attribute
 - RFC 4456 BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP)
 - RFC 4760 Multiprotocol Extensions for BGP-4
 - RFC 7432 BGP MPLS-Based Ethernet VPN
-

MIBs

- RFC 1213 MIB II
 - RFC 1907 SNMPv2 MIB
 - RFC 2571 SNMP Framework MIB
 - RFC 2572 SNMP-MPD MIB
-

Technical Specifications

- RFC 2573 SNMP-Notification MIB
 - RFC 2573 SNMP-Target MIB
 - RFC 2574 SNMP USM MIB
 - RFC 2737 Entity MIB (version 2)
 - RFC 3414 SNMP-User based-SM MIB
 - RFC 3415 SNMP-View based-ACM MIB
 - LLDP-EXT-DOT1-MIB
 - LLDP-EXT-DOT3-MIB
 - LLDP-MIB
-

Network Management

- RFC 2580 Conformance Statements for SMIv2
 - RFC 3164 BSD syslog Protocol
-

QoS/CoS

- IEEE 802.1p (CoS)
 - RFC 2475 DiffServ Architecture
 - RFC 2597 DiffServ Assured Forwarding (AF)
 - RFC 3247 Supplemental Information for the New Definition of the EF PHB (Expedited Forwarding Per-Hop Behavior)
 - RFC 3260 New Terminology and Clarifications for DiffServ
-

OSPF

- RFC 1587 OSPF NSSA
 - RFC 2328 OSPFv2
 - RFC 3101 OSPF NSSA
 - RFC 3137 OSPF Stub Router Advertisement
 - RFC 3623 Graceful OSPF Restart
 - RFC 4577 OSPF as the Provider/Customer Edge Protocol for BGP/MPLS IP Virtual Private Networks (VPNs)
 - RFC 4811 OSPF Out-of-Band LSDB
 - Resynchronization
 - RFC 4812 OSPF Restart Signaling
 - RFC 4813 OSPF Link-Local Signaling
-

Security

- RFC 1321 The MD5 Message-Digest Algorithm
 - RFC 2818 HTTP Over TLS
 - RFC 6192 Partial Support-Protecting the router control plane
 - ACLs SSHv2
-

Summary of Changes

Date	Version History	Action	Description of Change
06-Jul-2021	Version 18	Changed	SKUs added in Related Options section.
12-Oct-2020	Version 17	Changed	Related Options section was updated. MD
05-Oct-2020	Version 16	Changed	Configuration Information section was updated.
10-Aug-2020	Version 15	Changed	Configuration Information section was updated.
06-Jul-2020	Version 14	Changed	Configuration Information section was updated.
04-May-2020	Version 13	Changed	Configuration Information and Related Options sections were updated.
06-Apr-2020	Version 12	Changed	Configuration Information section was updated.
18-Nov-2019	Version 10	Changed	Configuration Information section was updated. New SKUS were added.
03-Sep-2019	Version 9	Changed	Configuration Information and Additional Options sections were updated. Obsolete SKUs were removed. New SKUs were added.
13-May-2019	Version 8	Changed	Added JQ075A, and, JQ077A, Multiple SKUs were added in Related Options Overview, Standard Features and Technical specifications sections were updated
02-Apr-2019	Version 7	Changed	Configuration was updated. Compatibility rules were updated.
18-Feb-2019	Version 6	Changed	Accessories updated
03-Dec-2018	Version 5	Changed	Configuration and Technical Specifications updated.
01-Oct-2018	Version 4	Changed	HPE Recommended Options section removed
04-Sep-2018	Version 3	Changed	Technical Specifications and Configuration sections were updated.
09-Aug-2018	Version 2	Changed	Technical Specifications section was updated.
06-Aug-2018	Version 1	New	New QuickSpecs

Copyright

Make the right purchase decision. Contact our presales specialists.



Chat



Email



Call



© Copyright 2021 Hewlett Packard Enterprise Development L.P. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

sFlow is a registered trademark of InMon Corp. All other third-party trademark(s) is/are property of their respective owner(s).

To learn more, visit: <http://www.hpe/networking>



a00047323enw - 16266 - Worldwide - V18 - 06-July-2021